



## Radio Communication Equipment

# HF - VHF - UHF SWR / POWER Meters



### Features

- \* High performance, large, cross needle meter display
- \* Simultaneously displays forward and reflected power and VSWR ratio
- \* True directional coupler for increased accuracy
- \* LED backlighting for smooth illumination
- \* Bright and easy to read 3 colour scale
- \* Can indicate either average power or PEP

MODEL NO:	RX-103	RX-203	RX-403	RX-503
Frequency Range	1.6-60MHz	1.8-200MHz	125-525MHz	1.8-525MHz
Power Range	0-2kW	0-200W		
Power Scale	20/200/2kW	2/20/200W		
Maximum Power	2kW	200W		
Accuracy: LOW Power	(AVG) +/- 10%, (PEP) +/- 15%			
Accuracy: HIGH(2)PWR	(AVG) +/- 5%, (PEP) +/- 10%			
Minumum PWR for SWR	3 Watts			
Input/Output Connectors	SO-239 (needs PL-259 Plugs)			
Weight (Net)	780g	790g	800g	950g
Insertion Loss	Less than 0.1dB			
Testing Function	Forward/Reflected Power, PEP, SWR			
Input/Output Impedance	50 Ohm			
Dimension (W/H/D) mm	140 x 84 x 122			
Accessories	Users operating manual, 13V DC Cable			

