



MARS/CAP and FREEBAND MOD for VX-7R

Author: Rick Jones

1. Remove the battery pack.
2. Remove the sticker/cover seal for the pressure sensing unit (SU-1), in the battery compartment. This is the black strip above cellular warning label and is where the SU-1 option goes.
3. Locate row of eight jumpers. They are numbered.
4. For Mars/Cap, remove solder jumper 5.
5. For Freeband, remove solder jumper 4 and 5.
6. Reset microprocessor. (Press and hold in the 4, band, and v/m keys while turning the radio on.
7. ENJOY

TX Frequencies:

Freeband: 40-224.995Mhz and 300-579.995Mhz

Mars/Cap: 50Mhz-54Mhz, 140Mhz-174Mhz, 222Mhz-225Mhz, and 420Mhz-470Mhz.

Rick Jones

This article is printed with permission from mods.dk the 25-11-2008. This printed article must only be used for non-commercial purposes; this is only for private use.

© Copyright mods.dk 1996 - 2008