

# IC-M33



#### Easy to see LCD with large channel indication

The IC-M33 has an easy to see LCD (32× 16 mm) with a clear 2-digit channel number indication. The Volume and SQL lev-

els are shown in the display. LCD and key backlighting is standard for night time operation.



# Easy to use, easy to hold

9 large buttons on the front panel provide simple straight forward operation. Weighing only 300g, and the IC-M33's easy-to-hold rounded body fits comfortably in your hand.

#### Quick channel selection with **Favourite channel function**

Tag your favourite or often used channels then push the "Fav" button, and easily recall those channels, while ignoring untagged channels.

Li-lon battery and charger standard A Lithium-Ion battery pack and battery charger are supplied as standard. The BP-252 Lithium-Ion battery pack provides 9 hours\* of operating time.

\* Typical operation with Tx (Hi): Rx: standby=5:5:90

### AquaQuake draining function

The AquaQuake draining function emits a vibrating sound and clears water away from the speaker grill.

Optional speaker-microphone, HM-165 The new optional waterproof speaker-microphone HM-165 will still allow the IC-M33 to float when attached. You will get great audio from it as well.

#### Other features

- Powerful 5W output power
- Dual/Tri-watch functions
- 4-step battery life indicator
- 2-step power saver
- 70 programmable channels
- Auto scan function
- Instant access to Ch 16 or programmable call channel
- · Optional battery case for using with alkaline cells (Also floats when connected to the IC-M33)

#### **SPECIFICATIONS**

#### GENERAL

Frequency range

156.000-161.450MHz Marine Rx

156.000-163.425MHz : INT, USA\* channels; Usable channels

(\* Depending on version)

• Current drain (at 7.4V DC, approx.) : 5W output 1.5A Τx

1W output 0.7A AF max. 200mA typical • Operating Temp. range : -15°C to +55°C

 Antenna impedance 50Ω (STUD) • Dimensions (W×H×D) : 61×140×43 mm

(projections not included)

 Weight (approx.) : 300g (with BP-252 and ANT)

#### TRANSMITTER

 Output power : 5/1W FRG version

1/0.5W Max. frequency deviation: ± 5.0kHz

Audio harmonic distortion: Less than 10% (at 60% dev.)

 Frequency error : ± 1.5kHz Spurious emissions : Less than 0.25uW

 Adjacent channel power : 70dB . Hum and noise ratio : 40dB

#### RECEIVER

• Sensitivity (20dB SINAD) : -2dBµ emf typical

: -5dBµ emf typical (threshold) Squelch sensitivity

· Adjacent Ch. selectivity: 70dB Spurious response. · 70dB

Measurements made in accordance with EN301-178-2. All stated specifications are subject to change without notice or obligation.

Intermodulation rejection: 68dB

Hum and noise ratio

· Audio output power : 0.2W (at 10% distortion with

an  $8\Omega$  load)

## Supplied accessories



- Battery pack, BP-252
- Battery charger, BC-173
- AC adapter, BC-174E
- Belt clip, MB-109
- Antenna, FA-SC58V (\* Not supplied depending on version.)
- Hand strap

**OPTIONS** 

Some options may not be available in some countries. Please ask your dealer for details.



BP-251 BATTERY CASE Battery case for AAA (LR03)×5 alkaline cells. Output power: 2W.

BP-252 7.4V/980mAh Li-Ion BATTERY PACK Provides 9 hours operating time (approx.). (Typical operation with Tx (Hi): Rx: standby=5:5:90)



**BC-173** DESKTOP CHARGER + BC-174E AC ADAPTER Regularly charges the battery pack, BP-252 in 10 hours (approx.).



**BC-162** DESKTOP CHARGER + BC-145E/UK AC ADAPTER Rapidly charges the battery pack, BP-252 in 2 hours (approx.).



HM-165 SPEAKER-MICROPHONE Waterproof construction equivalent to IPX7 (1 m depth for 30 min.).



MB-109 BELT CLIP Alligator type Same as supplied.

Les spécifications et informations données dans ce document peuvent être modifiées sans préavis.

#### ICOM FRANCE

Zac de la Plaine - 1, Rue Brindejonc des Moulinais BP 45804 - 31505 TOULOUSE CEDEX5 Tél: 05 61 36 03 03 - Fax: 05 61 36 03 00 WEB ICOM: http://www.icom-france.com E-mail: icom@icom-france.com





**CACHET REVENDEUR** 

